# SRD991 Intelligent Positioner with HART, PROFIBUS-PA, FOUNDATION Fieldbus H1 or Without Communication



The intelligent positioner SRD991 is designed to operate pneumatic valve actuators and can be operated from control systems (e.g. the Foxboro I/A Series System), controllers or PC-based configuration- and operational tools such as FDT/DTM Software. The positioner is available with different communication protocols. The multi-lingual full text graphical-LCD in connection with the 3 push buttons allows a comfortable and easy local configuration and operation. For installations in contact with explosive atmospheres, certificates are available.

### **DEVICE FEATURES**

### Intelligent

- · Auto-start with self-calibration
- Self diagnostics, status- and diagnostic messages
- · Easy operation with three key pads
- Multi-Lingual full text graphical LCD
- VALcare™ or Valve Monitor DTM for valve diagnostics and predictive maintenance

#### With communication

- HART, FOUNDATION Fieldbus H1, PROFIBUS-PA
- Configuration by means of local keys, handheld terminal (HART), PC with FDT-DTM or I/A Series system

### Without communication

Input signal 4 to 20 mA

### **COMMON FEATURES**


- Stroke 8 to 260 mm (0.3 to 10.2 in) with standard lever; larger stroke with special lever
- Angle range up to 95° (up to 300° as option)
- Supply air pressure up to 6 bar (90 psig), with spool valve up to 7 bar (105 psig)
- Single or double-acting
- Mounting on linear actuators according to NAMUR
   IEC 50534-6-1 VDI/VDE 3847
- Mounting on rotary actuators acc. to VDI/VDE 3845 or IEC60534-6-2
- Protection class IP 66 and NEMA 4X
- Approved for SIL applications
- Explosion protection: Intrinsic safety according to ATEX / IECEx, FM, CSA, INMETRO, NEPSI, EAC, ...



Contents	Page
Special Versions of SRD991	4
Common technical data for all basic device	<b>ces</b> 5
Operation, Diagnostics, Service plug	
Electricalclassification	9
Extended technical data for basic devices	<b>3</b> :
With communication HART	10
With communication PROFIBUS	
or FOUNDATION Fieldbus	11
• Basic device without communication (4-20	mA) 12
Additional equipment for basic devices	13
(built into the basic device)	
• Pressure sensors for premium diagnostics.	13
One Option board with additional inputs / out	puts:
• 2 Binary inputs or	14
• 2 Binary outputs or	15
• 2 Binary in/outputs or	16
Position feedback and Alarm or	17
Entry for remote Potentiometer	18
Additional built-in	
Limit signal switch	19

Contents	Page
FUNCTIONAL DESIGNATIONS	21
MODEL CODES SRD991	22
ACCESSORIES for mounting to the positione • Booster • Manifolds • Gauge manifolds	
ATTACHMENT to actuators	27
DIMENSIONS	31

### Electronics version: Communication HART, PROFIBUS PA, FOUNDATION Fieldbus or "without communication"



SRD991 3

### **OVERVIEW**

The SRD991 consists of a basic device with a digital controller that supports different communication protocols (or also simply 4-20 mA input). Into this basic device, additional equipment can be built such as plug-in cards for electrical input/output signals, position feedback and pressure sensors.

The pneumatic part is available in different versions (single / double acting or spool valve). For very large actuators, boosters with increased air capacity can be flanged on. Also, different manifolds for connection of gauges can be flanged on. For the pneumatic screw connections, we offer different threads in the housing and adapters.

For use in hazardous areas, there are approvals according to ATEX / IECEx, FM, CSA, EAC, NEPSI, etc.

The device can be configured locally by means of push buttons and LCD / LED, or with PC + EDC82 Modem connected to the service plug of the SRD991. By means of communication, the device can be configured remotely via FDT/DTM.

A large variety of attachment kits for all common valves and actuators are available. The list "AttachmentKits.pdf" is updated continuously and can be found on the Internet.

For high temperature or high vibration application, we recommend to mount the SRD991 remotely and not directly on the valve. For this, use the potentiometer unit (like the SRI990 - TXQxxxxx - H). Please consult TI EVE0105 R for specifications.

To ensure the high performance of the positioner, we offer Advanced Diagnostics and Premium Diagnostics utilities:

	Premium Diagnostics	Advanced Diagnostics
Autostart	Yes	Yes
Custom Characterization	Yes	Yes
Autodiagnostic	Yes	Yes
Alarm Management	Yes	Yes
Alarm Output for Switching (with Optionboard)	Yes	Yes
Status List acc. NE107	Yes	Yes
Position History	Yes	Yes
Response History	Yes	Yes
On Line Friction	Yes	
Stepping Signature	Yes	
Ramping Signature	Yes	
Sensitivity Signature	Yes	
Valve Signature	Yes	
PST (Partial Stroke Test)	Yes	
PST Predictive Maintenance	Yes	

### Additional equipment, built into the basic device:

Option Board "2 Binary Inputs" or	В	2 external switches (supplied by SRD) release a control function in the SRD, e.g. "close valve" (configurable)
Option Board "2 Binary Inputs/Outputs" or	Е	2 channels, each configurable as an input or output (to be supplied externally)
Option Board "Position Feedback"	F	1 output 4-20 mA (to be supplied externally) gives stroke / angle of rotation; 1 alarm output becomes active with a configurable event
Limit switch	T,U, R,V	Supplies NAMUR signals when exceeding or falling below of two limit values. Inductive sensors, independent of the controller, in normal or safety version or three-wire, or micro switches
		Entry for remote potentiometer of external potentiometer unit
Pressure sensors		2 sensors measure the pressure of supply air and output y1 for <b>Premium Diagnostics</b> ; the values are passed on via communication
LCD	-	Full text graphic LCD in 3 languages

Accessories like Manifolds and Boosters see page 24.

### **Special Versions of SRD991:**

### SRD991 Stainless Steel Housing

To be order with model code SRD991-xxxxxxxxx-Zxxx




Please consult TI EVE0105 INOX for specifications. For dimensional drawings see page 33.

### SRD991 for Top Mounting onto small actuators

This version is designed for direct mounting on top of small actuators without yoke - solution for actuators up to 50 mm stroke.

Instead of the rotary potentiometer, a linear pot is used that feeds back the actual position of the actuator.



The Model Code of this basic device is SRD991- ............-W

The adapter part is dependent on the manufacturer and type of actuator and can be ordered under the code EBZG-TMxx.

Please consult TI EVE0105 TM for specifications.

### SRD991 designated for PST (Partial Stroke

Test for Emergency Shut Down)


Final control elements in Emergency Shutdown (ESD) applications such as ON-OFF-, Blow Down and Venting valves remain in one position over a long time without any mechanical movement. These valves can show a tendency to get stuck and as a result might not operate upon demand. This can have a severe impact on the functionality of a Safety System and could result in an adverse condition to the operating personnel, plant equipment and the environment. The Partial Stroke Test (PST) offers operators a tool to identify the troubleshooting function of ESD valves. The test can be easily executed via the FDT-DTM based configuration diagnostic tool VALcare™/Valve Monitor.



Please consult TI EVE0105 PST.

### SRD991 for actuator with rotation up to 300°

This special version of the SRD991 is designed to be mounted by means of standard attachment kit (like the EBZG-R) onto rotary actuator with rotation up to 300°. This special version is made of a standard SRD991 with special gears.



To be ordered under Options -J. Please consult TI EVE0105 LR.

### FUNCTIONAL SPECIFICATIONS (common data for all versions)

### Travel range

Stroke range . . . . . . . . 8 to 260 mm (0.3 to 10.2 in) with standard feedback levers; special levers on request Rotation angle range . . . . . up to 95° without mechanical stop; up to 300° with Option –J.

### Supply

Supply air pressure . . . . . 1.4 to 6 bar (20 to 90 psig) with spool valve <sup>1)</sup> . . . . 1.4 to 7 bar (20 to 105 psig)

Output to actuator . . . . 0 to ~100 % of supply air pressure (up to 5.5 bar at 6 bar supply air pressure) with spool valve heavy duty<sup>2)</sup>: 4 to 10 bar

Air supply..... according to ISO 8573-1

- Solid particle size and density class 2
- Oil rate . . . . . . . . . . class 3
- Pressure dew point 10 K under ambient temperature The use of filter regulator for air supply of positioner is strongly recommended. It reduces the air pressure to actuator's maximum pressure and keeps it constant.

For supply with Natural Gas instead of compressed air please consult TI EVE0105 G.

### Air output In/h (scfh)

at max. deviation, single and double acting:

Supply air pressure bar (psig)	1.4	3	6
	(20)	(45)	(90)
Standard	2 700	5 000	7 500
Amplifier	(95)	(177)	(265)
with Spool	6 000	12 000	18 000
Valve 1)	(211)	(423)	(636)

<sup>&</sup>quot;Heavy duty" spool valve  $^2$  is able to deliver up to 55,000  $I_n/h$  at 10 bar. Please consult TI EVE0105 INOX.

Note: The use of boosters in connection with Spool valve is not recommended.

### Air consumption (steady state) I<sub>n</sub>/h (scfh)

will be incumplied (cloudy clairs) if it (com)			
Supply air pressure bar (psig)	1.4	3	6
	(20)	(45)	(90)
single acting	80	130	220
	(2.8)	(4.6)	(7.8)
double acting	130	230	430
	(4.6)	(8.1)	(15.2)
Spool	100	240	500
Valve	(3.5)	(8.5)	(17.7)

# Response characteristic 3)4)

Sensitivity ..... < 0.1 % of travel span

Non-linearity (terminal

based adjustment) . . . < 0.4 % of travel span
Hysteresis . . . < 0.3 % of travel span
Supply air dependence . . < 0.1 % / 1 bar (15 psi)
Temperature effect . . . < 0.3 % / 10 K

Mechanical vibration

10 to 60 Hz up to 0.14 mm,

60 to 500 Hz up to 2 g . . . . . < 0.25 % of travel span

### Volume Booster Series (to order as accessory)

For large actuators or to reduce action time, a volume booster may be necessary.

#### **VBS100 / VBS110**

Volume boosters with Cv1 and pneumatic connection 1/4", for remote mounting


VBS100 in Aluminium, VBS110 in Stainless Steel 316



For more information please consult PSS EVE0601.

#### VBS200 / VBS201 / VBS202

Volume booster with Cv 2 and pneumatic connection 1/2", for direct side mounting to positioner, remote mounting, or mounting acc. to VDI/VDE 3845




For more information please consult PSS EVE0602.

### VBS300 / VBS310

Volume boosters with Cv7 and pneumatic connection 1", for remote mounting

VBS300 in Aluminum, VBS310 in Stainless Steel 316



For more information please consult PSS EVE0603.

- 1) Spool valve is the type of amplifier used in device SRD991-Cxxxxx-S
- Spool valve heavy duty is the amplifier used in stainless steel version SRD991 - Cxx... - SZK
- 3) Data measured according to VDI/VDE 2177
- 4) With stroke 30 mm and lever length 90mm

### FUNCTIONAL SPECIFICATIONS (common data for all versions)

#### **Features**

Automatic start-up . . . . . . (Autostart functionality)
Automatic determination of the mechanical end positions of the valve (initial value and final value), IP motor parameters, direction of action of the spring and control parameters.
The control parameters are optimized dynamically during this routine.

This procedure makes a perfect adjustment and optimization to the actuator possible without additional manual settings! Several autostart modes are available (details see on next page).

### **Options**

- · Built-in independent inductive limit switches
- Pressure sensors for monitoring of air supply and output pressure I (y1)
  - Additional inputs / outputs:
    - Position feedback 4-20 mA + binary alarm output, to be supplied external
    - 2 binary outputs (position alarms)
    - · 2 binary inputs, to be supplied external
    - 2 contact inputs, internal supplied
    - · 2 binary in-/outputs, to be supplied external

### **Operation and Configuration**

The local LCD enable a fast and easy configuration as well as diagnostic.

The positioner in the version with LCD contains three different menu languages. Standard menu languages:

- English
- German

Freely selectable third language:

- French Portuguese Spanish
- Italian Swedish ...

(further menu languages see Model Code page 23).

The third menu language has to be selected and specified with the order, otherwise standard: French.

The third, freely selectable menu language can be modified to another language by means of the VALcare<sup>™</sup> DTM. <sup>2)</sup> The additional languages can be downloaded from our homepage.

### **Diagnostics**


- in the field:
- · Status and Diagnostic messages via LCD
- via VALcare™ or Valve Monitor DTM 4):
- Service Management for planning and scheduling of service intervals
- Histograms for displaying the position- and responsehistory over time
- Partial Stroke Test for the functional inspection of safety related actuators
- Hours in operation, cycle counter and travel sum of the actuator are determined
- · Surveillance of loop current

- · Shows condition of device:
- Potentiometer
- IP Motor
- Exceeding range of actuator (possible indication for wear of plug or seat)
- Remaining control deviation (possible indication for jammed actuator, blocked valve stem or plug, insufficient.
   air capacity /supply air pressure /positioning pressure)
- If equipped with pressure sensors (optional, see page 3):
- · Monitoring of the stem friction
- · Histograms for displaying the friction-history over time
- Surveillance of air supply and output pressure, each with display of physical value
- Additional diagnostical possibilities in control operation by means of external sensors (optional).
   See also the VALcare™ Documentation.

### Service plug

All basic devices are equipped with a service plug **A** at the front side. There via RS232 interface a PC with VALcare (DTM) can be connected via modem EDC82 (galv. separated, not Ex).

Information about EDC82 modem see TI EVE0102 Y.



- With the versions "Intelligent without communication" this is only possible with modem EDC82
- By means of "Additional inputs / outputs"
- For the SRD991 without communication the use of the service plug is necessary to have access at the diagnostic with DTM

PSS EVE0105 E-(en) SRD991

# Manual local and remote settings:

Actuator mode	linear or rotary actuator
Linear valve	left or right mounted
Rotary actuator	opening clockwise or
•	counter-clockwise
Characteristic of setpoint	linear, equal percentage.
·	invers-equal percentage
	or custom (22 points)
Valve function	
valve landaen	increasing setpoint
Split range	
	free upper and lower values
Cutoffs	
Stroke range	
Temperature unit	configurable (°C or °E)
Autostart	- Endpoints
Autostart	- Standard Autostart
	- Enhanced Autostart
	- Smooth response
Control novementors	- Fast response
Control parameters	
Working range	
	indication on LCD)
Manual adjustment of	P-gain, I-time,
	T63-time and dead band
Manual operation	
	drive the valve in steps of
	12.5%, 1% or 0.1%
Pneumatic test	
	matic output
Workshop	
LCD language	
LCD orientation	
PROFIBUS-PA	
FOUNDATION Fieldbus	Simulation
	Switch from Link Master to

Basic Field Device

### Software supported configurations:

- By means of Hand Held Terminal (HART)
- PC by means of VALcare Software
- I/A Series System, Foxboro Evo and other DCSs

### Failure handling

In case of Single Acting, Safety position at
- Air supply failure . . . . . pressure y1 = zero
- Electric power failure . . . . pressure y1 = zero
- Failure of electronics . . . . pressure y1 = zero
In case of Double Acting or spool valve amplifier,

safety position at

- Air supply failure . . . . . . pressure y1 = zero / y2 = zero

- Electric power failure . . . . pressure y1 = zero / y2 =
full air supply pressure

- Failure of electronics . . . . pressure y1 = zero / y2 =
full air supply pressure

For all types of amplifiers (with FF H1 or Profibus PA)

- Failure of communication is recognized by configurable watch dog with response delay of 0.1 s to 24 h

Behavior . . . . . . . . . configurable as - pressure y1 = zero or

stop at last value or
a configured value

Diagnostic report . . . . . . via communication and local

LCD

- Historical status . . . . . . . is set if alarm was activated at any time (also just short alarms)

Reset . . . . . . . . . by acknowledging

# Spool Valve Amplifier for single and double acting

Spool valve amplifier as option for the SRD991 can be used with double acting actuator and also with single acting actuator.

In case of single acting application, one of the pneumatic output must be closed:

- If y1 is used, y2 is closed and failure handling for Electric power failure and Failure of electronics becomes y1=zero.
- If y2 is used, y1 is closed and failure handling for Electric power failure and Failure of electronics becomes y2=full air supply.

# FUNCTIONAL SPECIFICATIONS (common data for all version)

FUNCTIONAL SPECIFICATIONS (common data for all version)			
Mounting Attachment to stroke actuators - direct, FlowPak/FlowTop with attachment kit EBZG –E	Ambient conditions  Operating conditions acc. to IEC 654-1  The device can be operated at a class Dx location  Ambient temperature		
- for casting yoke acc. to IEC 534-6 (NAMUR) with attachment kit EBZG –H or –H1	Operation <sup>1)</sup>		
- for pillar yoke acc. to IEC 534-6 (NAMUR) with attachment kit EBZG –K or –K1	above 80 °C, we recommend a sun shade.  Storage conditions acc. to IEC 60721-3-1: 1K5; 1B1; 1C2; 1S3; 1M2		
Stroke range with feedback lever: - standard (EBZG-A) 8 to 70 mm / 0.31 to 2.76 in - extended (EBZG-B) 60 to 120 mm / 2.36 to 4.72 in - extended (EBZG-A1) 110 to 260 mm / 4.33 to 10.24 in Larger stroke ranges can be realised with special levers.	Indicators  LCD (visible) <sup>2)</sup>		
Attachment to rotary actuators acc. to VDI/VDE 3845	acc. to IEC 60529 IP 66 acc. to NEMA Type 4X		
with attachment kit EBZG -R - Further attachment kits see ModelCodes page 26 - Mounting orientation see attachment dimensions starting from page 27	Electromagnetic compatibility EMC Operating conditions industrial environment Immunity according to EN 61326 fulfilled		
Materials	IEC 61326 fulfilled EN 61000-6-2 fulfilled		
Housing and covers Aluminum (Alloy No. 230) finished with DD-vamish	Emission according to EN 61326		
All moving parts of feedback system	Class A and Class B fulfilled EN 61000-6-4 fulfilled EN 55011 Group 1,		
(depending upon version) (Alloy No. 230)  Mounting bracket Aluminum (Alloy No. 230)  Pneumatic diaphragms PVMQ (Silicone elastomer suitable for use in the paint industry)	Class A and Class B fulfilled  NAMUR recommendation  EMV NE21 fulfilled		
Weight	SAFETY REQUIREMENTS		
Single acting approx. 1.7 kg (3.7 lbs)  Double acting approx. 2.0 kg (4.4 lbs)	CE label Electromagnetic		
Pneumatic connection  NAMUR mounting G 1/4 for pipe diameter 6 to 12 mm (0.24 to 0.47 in) for air supply and outputs y1, y2 to the actuator; 1/4-18NPT with additional connection manifold  Direct mounting and leaded of the output y1, and	Compatibility <sup>4)</sup>		
Direct mounting Instead of the output y1, an air connection on the back with O-ring will be used (closed at NAMUR mounting).	Overvoltage Category I Internal fuses only with PROFIBUS or FOUNDATION Fieldbus,		
Electrical Connection  Line entry	but not replaceable External fuses Limitation of power supplies for fire protection must be observed acc. to EN 61010-1, appendix F (or IEC 61010-1).		
crimped wire 0.5 to 2.5 mm² (AWG 21-14)  Test sockets integrated in terminals, for options and communicator connection	<ol> <li>Details see Certificates of Conformity.         With Limit Switches Code T only –20 °C.         With Limit Switches Code R only –25 to 70 °C         Below –20 °C the LCD reacts only slowly; above 70 °C the background becomes dark         Under service as directed         With PROFIBUS or FOUNDATION Fieldbus only, if shield of wiring is grounded on both sides</li> <li>Pneumatic connection 1/4-18 NPT made with a seperate manifold</li> </ol>		

delivered together with the device

# SRD991 **9**

### Electrical classification 1) 2)

See Certificates of Conformity EX EVE0105 A

# Type of protection "Intrinsically Safe" ATEX / IECEx

Marking ...... Ex ia IIC T4 Gb, Ex ia IIC T6 Gb

Temperature classes

Version with HART communication and "without communication":

T4 with explosion protection code EA4

Version with communications HART, FOUNDATION Fieldbus and PROFIRI IS-PA

T4 / T6 with explosion protection code EAA

Certificate of Conformity ...... IECEx EPS 16.0034

EPS 16 ATEX 1 083

For use in hazardous areas in circuits certified as intrinsically safe with the following maximum values:

Profibus / Fieldbus			HART	
Ui	24 V DC	Ui	30 V DC	
li	380 mA	li	130 mA	
Pi	5.32 W	Pi	0.9 W	
Ci	1.3 nF	Ci	1.3 nF	
Li	5 µH	Li	5 µH	

Ci: effective inner capacity

Li: effective inner inductivity

The supply connections have an inner capacity of max. 5.3 nF opposite the ground.

Ambient temperature ranges:

Temperature class T4: .... –40 °C to 80 °C Temperature class T6: .... –40 °C to 55 °C

### Explosion protection Zone 2/22

Installation of the SRD991 in potentially explosive atmospheres for Zone 2 / 22 (explosion protection II 3 G/D Ex ic Gc/Dc)

The Intelligent Positioner SRD991 in protection level intrinsic safety "ic" (II 3 G/D Ex ic Gc/Dc) can also be operated in potentially hazardous areas of Zone 2 / 22.

### **Explosion protection Zone 20**

EX II 1D Ex ia IIIC T 100°C Da. . . . . -40 °C < T<sub>a</sub> < 100 °C

Electrical Data

Supply circuit in type of protection Intrinsic safety Ex ia.

The positioner type SRD991 fulfils the requirements of explosion protection for the Equipment Group II and Category 1D in type of protection Intrinsic safety for dust with a maximum surface temperature of 100 °C.

### **FM Type of protection**

IS / I,II,III / 1 / ABCDFG / T4 Ta = 80°C, T6 Ta = 55 °C Entity; Type 4X; DOKZ 534 396 049 NI / I / 2 / ABCD; S / II,III / 2 / FG / T4 Ta = 80 °C, T6 Ta = 55 °C; Type 4X


### **CSA**

PROCESS CONTROL EQUIPMENT-Intrinsically Safe, Entity - For Hazardous Locations Class I, Groups, A, B, C and D; Class II, Groups E, F and G; Class III:
Ex ia IIC T4/T6 IP65:

SRD 991 HART/4-20mA/FOXCOM/Profibus/Fieldbus-abcdefgh-j Positioner: 12-36 V dc, 4-20 mA or < 48 V dc, Intrinsically safe when installed as per submittor's Dwg DOKZ 534 396 067 or DOKZ 534 396 076; Temp. Code T4 at Max Amb. 80C or T6 at Max Amb. 55C.</li>

Note: Model No is followed by suffix abcdefgh-j denoting minor mechanical differences and options not affecting safety.

With Electrical Classification ATEX + Zone 20 Dust, Codes ED4 and EDA, the Travel indicator is not visible.



- 1) With appropriate order only
- 2) National requirements must be observed
- Standard has been replaced by a new standard or revision. The products are according to these new standards or revisions, because the modified requirements are not relevant.

# SRD991 with HART communication SRD991-xHxxxx

(Frequency Shift Key) modulated on 4-20 mA 0.5 Vpp at 1 kOhm load

Input impedance Zi. . . . . . Z = 320 Ohms

for ac voltage 0.5 to 10 kHz with < 3 dB non-linearity Cable capacity and inductance see HART standard specifications (e.g. C < 100 nF).

Impedance of other devices at the input (parallel or serial) must be within HART spec.

Applications without communication require not to exceed input capacitance parallel to the input not higher than 100  $\mu$ F.

Start-up time . . . . . . . . . approx. 3 sec Interruption time without power down:

with LCD . . . . . . . . . . typ. 80 ms <sup>2)</sup>

### Configuration

The SRD991 can be configured via HART by any host system whatever is a PC with a HART Modem, Hand Held Terminal or a DCS.

**LOCAL** (by means of local key pad and LCD display) See page 6

### **DTM** (Device Type Manager)

We are a leading company in term of FDT-DTM technology <a href="http://www.fdtgroup.org/product-catalog/certified-dtms?com">http://www.fdtgroup.org/product-catalog/certified-dtms?com</a> pany=Foxboro+Eckardt+GmbH&field device type value many to one=All&field protocol value many to one=All


Therefore we provide a DTM fully certified for its interoperability and with the state-of-the-art presentation and diagnostics features.

The DTM can be downloaded from our homepage.

# DD (Device Description) and EDD (Enhanced Device Description)

In case the host system is not supporting the FDT-DTM technology, you can download the DD and/or EDD from our homepage.

- 1) On request we can specify higher voltage limits
- Worst case conditions 4-20 mA, with position feedback option, i/p-output with max. current



PSS EVE0105 E-(en) SRD991

# SRD991 with communication PROFIBUS-PA and FOUNDATION Fieldbus H1 SRD991-xPxxxx or SRD991-xQxxxx

### **PROFIBUS-PA**

Data transfer ... according to PROFIBUS- PA
profile class B based on EN
50170 and DIN 19245 part 4
GSD file ... the actual file can be downloaded from our homepage

Configuration
Local / Display ... see page 6
Software ... VALcare™ -DTM
Hardware ... PC- or PCMCIA- interfaces
from Softing
I/A Series System ... FBM 223 in combination with

CP60
Other control systems . . . . All Profibus-PA- compatible,

e.g. Siemens SIMATIC PDM (Process Device Manager)

### **FOUNDATION Fieldbus H1**

Data transfer . . . . . . . FF Specification Rev. 1.4, Link-Master (LAS)

Two revisions of Firmware can be selected for the FOUNDATION Fieldbus devices in the model code of the positioner. The selection of the Firmware revision is depending of the DCS compatibility, the DD Files already installed in the DCS and the installed base on your site.

Double check interoperability of following characteristics with your DCS before ordering!

When selected Firmware FF16 in the model code:

Certified according to . . . . . ITK 4.6

Function Blocks . . . . . . PID, AO, 2xDI, 1xDO

Transducer, Resource

When selected Firmware FF18 in the model code:

Certified according to . . . . . ITK 6.0.1

Function Blocks . . . . . . PID, AO, 4xDI, 1xDO, IS, OS,

AI, MAI, Transducer,

Resource

Additional functionality . . . Flat Addressing

DD files . . . . . . . . . . . the actual file can be down-

loaded from our homepage

### Configuration

Hardware . . . . . FBUS-interfaces from National Instruments (AT-FBUS and

PCMCIA- FBUS

I/A Series System ..... FBM220 or FBM221 in

combination with CP60

Other control systems . . . . . All FOUNDATION Fieldbus

H1- compatible, e.g. SMAR, Fisher Rosemount Delta-V,

Honeywell, Yokogawa, ABB

### For both fieldbus devices

Input signal . . . . digital Supply voltage . . . . DC 9 to 32 V <sup>1)</sup> max. Supply voltage . . . . DC 36 V

Operating current . . . . . . . . 10.5 mA ± 0.5 mA (base current)

Current amplitude . . . . . . . ± 8 mA

Fault current. . . . . . . . . . . . . Base current + 0 mA (base current + 4 mA by means of independent FDE-safety circuit) according to IEC 1158-2

Operating values . . . . . . . according to IEC 1158-2

Start-up time (init phase) . . . approx. 2 sec

Bus connection . . . . . . . Fieldbus interface based on

IEC 1158-2 according to FISCO-Model

Power supply . . . . . . . Power supply is achieved dependant on the application by means of fieldbus

power supply units or segment coupler

### **Electrical classification thereto**

see page 9

# SRD991 without communication SRD991-xDxxxx

### Configuration

Local / Display	see page 6
Software	VALcare™ (DTM)
Hardware	per modem EDC82

### **Electrical classification thereto**

see Page 9

- 1) Data of "Intrinsically Safe" version
- 2) On request we can specify higher voltage limits
- Worst case conditions 4-20 mA, with position feedback option, i/p-output with max. current

# **OVERVIEW ADDITIONAL EQUIPMENT**

(built into any basic device)


# **Built-in Pressure sensors for Premium Diagnostic,** Code Option –B

For supply air and output y1 to actuator

Measuring range . . . . . . . 0 to 8 bar (0 to 120 psig)


Accuracy . . . . . . . . . . . . 2 %

Temperature influence . . . . 0.5 % / 10 K (–40 to 80 °C)



### **Additional Inputs / Outputs:**


One module "Additional inputs / outputs" **8** can be plugged onto main electronics **40**:



- · 2 Binary inputs or
- 2 Binary in/outputs or
- Position feedback and Alarm Details see following pages.

### **Built-in Limit Switch**

Details see page 19



### Parts Kits for additional installation of auxiliary functions

Model codes, Additional inputs / outputs	Supply	Parts Kit
Code B: 2 Binary inputs (Contact inputs)	internal	EW 411 407 325
Code E: 2 Binary in/outputs	external	EW 411 407 956
Code F: Position feedback 4-20 mA and Alarm (ATEX)	external	EW 426 434 228
Model codes, Limit signal switches		
Code T: Limit signal switch, normal version	external	EW 426 164 012
Code U: Limit signal switch, security version	external	EW 426 164 021
Code R: Limit signal switch, 3-wire	external	EW 426 164 057
Code V: Limit signal switch, micro switches	external	EW 426 164 066
Code D: Entry for remote potentiometer	internal	EW 426 164 093

# ADDITIONAL EQUIPMENT built into any basic device

### Additional Inputs / Outputs: Two Binary (Contact) inputs – Code B

Two independent binary inputs, supplied with the basic device, for connection of external switches.

A connected switch is loaded with 3.5 V, 150  $\mu$ A.

This option 'Binary inputs' can also be used to activate PST (Partial Stroke Test).

The binary inputs can be used for diagnostics or are also configurable for the control functions:

-		
Switch 1	Switch 2	Actuator control function
close	close	normal operation
open	close	go to stop at 0 %
close	open	go to stop at 100 %
open	open	hold last position

Terminals for EB1 . . . . . . . K2/1 + : 13 K2/2 – : 14

EB2..... K3/1 + : 15 K3/2 - : 16

For further informationen about the contact inputs please consult TI EVE0105 B.

### **Electrical Classification ATEX / IECEx**

Types of protection and temperature classes of basic device, see page 9.

Additions for this option in EC-Certificate of Conformity IECEx EPS 16.0034 and EPS 16 ATEX 1 083:

To this electric circuit only passive electric circuits galvanically separated from earth may be attached.


The electric circuit has the following maximum values: Uo= 7.88 V, Io= 11.4 mA, Po= 23 mW

Characteristic is linear.

For the maximum values of outer inductances and capacities Lo and Co refer to the following table (Li and Ci included):

IIC		IIB		
Lo [mH]	Co [µF]	Lo [mH]	Co [µF]	
100	0.72	100	3.9	
10	1.1	10	5.5	
1	1.6	1	8.7	
0.1	2.7	0.1	15	
0.01	4.7	0.01	27	


The electric circuits of "2 binary inputs" are galvanically connected with all other circuits and isolated from earth.



One module "Additional inputs / outputs" **8** can be plugged onto main electronics **40**:

- 2 Binary inputs or
- · 2 Binary in/outputs or
- Position feedback and Alarm

### **DTM Configuration window**



# Additional Inputs / Outputs: Two binary in/outputs - Code E

This option board is recommended for PST applications.

### **Output:**

2 galvanically separated signals

Limit signals / alarms freely configurable via local keys or via communication.

Two-wire system, according to DIN 19234, for external supply.

supply voltage . . . . . . . . . DC 8 to 36 V 1) 2)

### Configured as NAMUR signal:

Logic:

Limit value not exceeded . . . < 1 mA Limit value exceeded . . . . typ. 6 mA Device fault . . . . . . < 50 µA

### Configured as On/Off signal:

Limit value not exceeded . . . < 50 µA

Limit value exceeded. . . . . . > 20 mA/20 V / > 40 mA/10 V

(power derated)

Reference: AB1 for upper, AB2 for lower limit value

Terminals for AB1 . . . . . . . K2/1 + : 81 K2/2 – : 82

AB2.....K3/1 + : 83 K3/2 - : 84

### Input:

The kind of Signals Input can be configured as On/Off or as NAMUR signal in accordance to (DIN 19234)

### Configured as NAMUR signal:

Unloaded supply voltage . . . > 8 V

Input

Configured as On/Off signal:

Input:

Logic 0. . . . . . . < 4 mA Logic 1. . . . . > 6 mA Signal Voltage Range . . . . 8 to 36 V<sup>1)</sup>


#### **Electrical Classification ATEX / IECEx:**

Types of protection and temperature classes as basic device, see page 9.

Additions for this option in EC-Certificate of Conformity IECEx EPS 16.0034 and EPS 16 ATEX 1 083:

For use in hazardous areas in circuits certified as intrinsically safe with the maximum values as described in the Certificate of Conformity in chapter "Option UNI-IO".


The circuits Channel 1 and Channel 2 are electrically safe separated from each other, from all other external circuits and from earth.



One module "Additional inputs / outputs" **8** can be plugged onto main electronics **40**:

- · 2 Binary inputs or
- 2 Binary in/outputs or
- Position feedback and Alarm

### **DTM Configuration window**



- 1) Other values in hazardous areas
- 2) On request we can specify higher voltage limits

# Additional Inputs / Outputs: - Code F Position feedback 4-20 mA and Alarm

with electrical classification ATEX / IECEx

Stroke / angle derivated from positioner feedback 1 output analog, galvanically separated, two-wire system according to DIN 19234, for external supply

Supply voltage . . . . . . DC 8 to 36 V <sup>1) 2)</sup>
Signal range . . . . . . . . 3.8 to 20.5 mA

0 % and 100 % configurable

Device fault . . . . . < 50 μA
Terminals for Al1 . . . . . K3/1 + : 83
K3/2 – : 84

Feedback signal can be reversed (20 --> 4 mA).

1 binary alarm output, galvanically separated, two-wire system, according to DIN 19234, for external supply

configurable as switch output:

Limit value not exceeded . . . < 50 µA

Limit value exceeded. . . . . . > 20 mA/20 V / > 40 mA/10

V (power derated)

K2/2 -: 82

The binary output for Alarm will be activated in the following cases:

- Remaining control deviation
- Circuit to I/P module is disturbed
- Circuit to potentiometer is disturbed
- Calibration error:
  - no angle calibration
  - no current calibration
- Autostart failed

These pre-settings can be configured via communication with the Alarm Link function in the DTM.


### **Electrical Classification ATEX / IECEx:**

Types of protection and temperature classes as basic device, see page 9.

Additions for this option in EC-Certificate of Conformity IECEx EPS 16.0034 and EPS 16 ATEX 1 083:

For use in hazardous areas in circuits certified as intrinsically safe with the maximum values as described in the Certificate of Conformity in chapter "Option UNI-IO".


The circuits Channel 1 and Channel 2 are electrically safe separated from each other, from all other external circuits and from the earth.




One module "Additional inputs / outputs" **8** can be plugged onto main electronics **40**:

- · 2 Binary inputs or
- · 2 Binary in/outputs or
- · Position feedback and Alarm

### **DTM Configuration window**





- 1) Other values in hazardous areas
- 2) On request we can specify higher voltage limits

### **Entry for remote potentiometer**

(for remote mounting main unit)

#### Code D

This remote application is used in applications where high temperatures or vibration are present and can result in negative influences to the control. It can also be used in places not easy to reach, to ensure an easier handling of the unit, or for cylinders with large strokes.

The Positioner SRD991 (Remote unit) is mounted far away from the valve or cylinder in a safe environment.

The Potentiometer unit is mounted on the valve or cylinder. This potentiometer unit can be made of a derivative version of the SRI990 positioner (only potentiometer in the housing) or of an external potentiometer like a linear potentiometer for application onto cylinders, for example.

This option is to be used with a potentiometer unit 3 wires system with approx. 5 kOhm resistance.

If the following requirements are observed, the set-up is insensitive to electrical disturbances caused by high electromagnetic fields, EMC and HF-radiation.

Cable Length max. . . . . . . . 10 m (32 ft)

Cable Specification (not supplied by us):

- · 3-wire twisted pair, shielded
- Shield needs to be connected on both ends to the internal ground
- Shield endings need to be kept very short when connecting to the ground
- · A HF cable gland is not required

For more information about remote mounting please consult TI EVE0105 R.

**Note:** The functionality and certifications are only ensured with our 5 kOhm potentiometer.

### **Electrical Classification ATEX / IECEx:**


Types of protection and temperature classes as basic device, see page 9.

Additions for this option in EC-Certificate of Conformity IECEx EPS 16.0034 and EPS 16 ATEX 1 083:

For use in hazardous areas in circuits certified as Intrinsically Safe with the following maximum values:

Umax = 6.5 V I\_supply = 25 mA I\_wiper ≤ 1 mA

P total ≤ 40 mW



PSS EVE0105 E-(en) SRD991

### **Built-in Limit Switches**

Stroke / angle derived from positioner feedback

- Standard version (SJ2-N) ...... Code T (only to -20°C)


- Security version (SJ2-SN).....Code U

- 3-wire  $\,$  (SI2-K08-AP7/ PNP)...Code R (no Ex, –25 to 70  $^{\circ}\text{C})$ 

- Micro switches (V4NS) ......Code V (no Ex)

- Entry for remote potentiometer Code D

### **Materials**



### Inductive Limit Switch (Code T, U)

Output . . . . . . . . . . . 2 inductive proximity sensors acc. to DIN 19 234 or NAMUR for connection to switching amplifier 1)

Current consumption

Vane clear . . . . . . . . > 2.2 mA Vane interposed . . . . . . < 1 mA

for control circuit with the following electrical values:

Supply voltage  $\,\ldots\,$  DC 8 V,  $R_i$  approx. 1 kOhm Supply voltage range. . . . . DC 5 to 25 V (with "no Ex")

Residual ripple . . . . . . . < 10 % p.p.

Permissible

line resistance . . . . . . < 100 Ohms

Response characteristic 2) 3)

Switching differential . . . . < 1 % Switching point repeatability < 0.2 % GW2 . . . . . . 51+, 52-

### **Electrical Classification ATEX / IECEx** of versions "T" and "U":

Types of protection and temperature classes as basic device, see page 9.

Additions for this option in EC-Certificate of Conformity IECEx EPS 16.0034 and EPS 16 ATEX 1 083:

For use in hazardous areas in circuits certified as Intrinsically Safe with the following maximum values:

Ui= 16 V, Ii= 25 mA, Pi= 64 mW

Internal capacitance and inductance: Ci= 30 nF, Li= 100 µH The electric circuits of "Built-in Limit Switch" are galvanically separated from all other circuits and from earth.

### Inductive Limit Switch, three-wire system

### Code R

Input . . . . . . . . . Stroke / angle from actuator via positioner feedback lever Output . . . . . . . . . . . . 2 inductive proximity sensors, three-wire system, LED indication, contact, pnp 2) Supply voltage U<sub>s</sub> . . . . . . . DC 10 to 30 V Residual ripple . . . . . . . .  $\pm$  10 %, U<sub>s</sub> = 30 V Switching frequency . . . . . . 2 kHz Constant current . . . . . . . . 100 mA Response characteristic 6)

Gain . . . . . . . . . . . . . . . continuously adjustable from 1:1 to approx. 7:1

Switching differential . . . . < 1 %

Switching point

repeatability. . . . . . . . < 0.2 % Terminals for GW1.....42 GW2.....52 Supply. . . . . . 41+, 43-

Mechanical Switches (Micro Switches) Code V

Stroke / angle derived from positioner feedback lever

Output . . . . . . . . . . . . 2 mechanical switches (Micro switches) 5) 6) Manufacturer . . . . . . . . . Saia-Burgess (UL- and CSA-approved)

Parts set for subsequent mounting:

Code V . . . . . . . . . . . . EW 426 164 066

Absolute limit values AC

(only without Ex protection)

of mechanical switches built into positioner: Umax......130 V AC 7)

Imax . . . . . . . . . . . . 0.5 A (resistive Load) 7) Imax ..... 0.03 A (inductive Load) 8)

Absolute limit values DC

of mechanical switches built into positioner: 9)

DC Imax . . . . . . . . . . . . 1 A

Switching Differential: . . . . < 2.5 % Terminals for SW1 . . . . . . . 41, 42 SW2.....51, 52

The circuit of the mechanical switches have to be protected by a suitable fuse. The diameter of the protective conductor needs to be at least 1.5 mm<sup>2</sup> / AWG 16.

Operating mode min. (= low) / max. (= high) selectable by adjustment of switch vanes

Data measured according to VDI/VDE 2177

With stroke 30 mm and lever length 90 mm

Operating mode min. (=low) / max. (=high) selectable by adjusting the respective vane


Operating mode normally open / normally closed selectable by vane adjustment

Approval according to UL (UL 1054) and CSA (CSA 22.2 No. 55) at 6,000 operations and T = 65 °C / 149 °F

Based on EN 61058-1, at 10,000 operations and T = 85  $^{\circ}$ C / 185  $^{\circ}$ F

General rating at 50,000 operations and  $T = 85 \,^{\circ}\text{C} / 185$ 

**SRD991** 



- 1a Adapter, eg. 1/2"-14 NPT
- 1b Cable gland
- Plug, interchangeable with Pos. 1
  Screw terminals <sup>1)</sup> (11 / 12) for input (w) or for bus connection IEC 1158-2
  Screw terminals <sup>1)</sup> for additional inputs / outputs
- 3b Test sockets Ø 2 mm, integrated in terminal block
- Ground connection 4
- Female thread <sup>G)</sup> 1/4 -18 NPT or output I (y1) Female thread <sup>G)</sup> 1/4 -18 NPT for air supply (s) Female thread <sup>G)</sup> 1/4 -18 NPT or output II (y2)
- 7
- Direct attachment hole for output I (y1) 8
- 9 Feedback shaft
- 10 Connection manifold for attachment to stroke actuators (not with VDI/VDE 3847 version)
- 11 Connection base for attachment to rotary actuators
- 12 Travel indicator

- Key **UP** 13
- Key DOWN 14
- Key M (Menu) 15
- Status display (1 red LED, 4 green LEDs)<sup>2)</sup> 16
- 16a LCD with true text in 3 different languages
- Fixing shaft for limit switch 19
- Cover with window to 12 20
- Air vent, dust and water protected 21
- Data label 22
- Arrow is perpendicular to shaft 9 at angle 0 degree 26
- Ball valve for protection class NEMA 4X 27
- High cover with built-in limit switch 28
- Plug for service connector 3)
- G) With marked letter "G" in the housing the pneumatic connecting threads are cut as G 1/4 instead of 1/4-18 NPT
- Alternatively Cage clamps (WAGO) instead of screw terminals
- Depending on the version, the device is equipped with or without LEDs

### **MODEL CODES SRD991**


290317 Intelligent Positioner **SRD991** Single Acting.....-B Double Acting .....-C Input/Communication HART Communication (4 - 20 mA)...... H PROFIBUS-PA (acc. to FISCO) ......P FOUNDATION Fieldbus H1 (incl. PID-Fct. Block, acc. to FISCO) ... Q Additional Inputs/Outputs Prepared For Additional In-/Outputs.....N Binary Inputs .....(z) .....B Binary Inputs-Outputs (mandatory for ESD application).....(z) ......E Position Feedback 4 - 20 mA and one Binary Output for Alarm ......F Without Built-In Limit Switch ......S Inductive Limit Switch - Intrinsically Safe (Standard Version SJ2-N) ......T Inductive Limit Switch - Intrinsically Safe (Security Version SJ2-SN)......U Inductive Limit Switch - Three wire version ......(u) ......R Mechanical Switches (Micro-Switches) / UL- and CSA-approved....... (u) ....... V Potentiometer Input - CEM Filter (for Remote Mounting - main unit) ..... (k) ........D Cable Entry M20 x 1.5 Without Cable Gland......1 1/2"-14 NPT (with Adapter(s) M20x1.5 to 1/2"-14 NPT)......6 **Electrical Classification** Without Ex ......ZZZ for Input/Communication D, H .....(y) for Input/Communication H, F.....(x) II 2 G Ex ia IIC T4 Gb according to ATEX / IECEx ......EA4 II 2 G Ex ia IIC T6 Gb according to ATEX / IECEx.....(d).......EAA II 3 G/D Ex ic T4 Gc/Dc according to ATEX.....(b)......(b)....... II 3 G/D Ex ic T6 Gc/Dc according to ATEX ......(b) ......(b) II 2 G Ex ia IIC T4 Gb + II 1D Ex iaD 20 T100°C Da acc. to ATEX / IECEx.(c) ......ED4 II 2 G Ex ia IIC T6 Gb + II 1D Ex iaD 20 T100°C Da acc. to ATEX / IECEx.(d).....EDA FM Nonincendive for Class I, Division 2, Groups A, B, C, D, Hazardous Locations Indoors And Outdoors, NEMA 4X ......NFM for Input/Communication D, H .....(y) FM Approved for Intrinsic Safety Class I, Division 1, Groups A, B, C, D, Hazardous Locations Indoors And Outdoors, NEMA 4X.....FAA for Input/Communication D, H .....(y) CSA Approved for Intrinsic Safety Class I, Division 1, Groups A, B, C, D, Hazardous Locations Indoors And Outdoors, NEMA 4X.....CAA for Input/Communication D, H .....(y) EAC Approved for Intrinsic Safety Ex ia IIC T4 ......(c) .......RU4 EAC Approved for Intrinsic Safety Ex ia IIC T6..T4.......(d)......RU6 NEPSI – Ex ia IIC T4/T6 Gb Ex iaD 20 T100°C IP65..... Attachment Kit Pneumatic connection G 1/4 ......R (continued on next page)

# 21

### MODEL CODES SRD991 (continued)

OPTIONS	
Premium Diagnostics Features (made with built-in Pressure Sensors). (v)	B
Positioner free of copper and its alloys(h)	C
Pneumatic Amplifier in the "Spool Valve" Version(n)	
Approved for SIL2 / SIL3 application(w)	Q
Custom Configuration	T
Version of Positioner according to VDI/VDE 3847	N
Version for ESD Valve with PST functionalities(a)	E
Rotating angle up to 300 °	
Stainless Steel Housing(f)(f)	
Stainless Steel Housing without SST gauges(f)	Z1
Stainless Steel Housing 10 bar supply(m)(m)	ZK
Stainless Steel Housing 10 bar supply without SST gauges(m)	-ZK1
Top Mounting version of SRD991 with built-in linear potentiometer (j)(l)	
LCD with Menu-Language in English / German / French	
LCD with Menu-Language in English / German / Spanish	
LCD with Menu-Language in English / German / Portuguese	
LCD with Menu-Language in English / German / Polish	
LCD with Menu-Language in English / German / Czech	
LCD with Menu-Language in English / German / Italian	-V06
LCD with Menu-Language in English / German / Turkish	
LCD with Menu-Language in English / German / Swedish	
LCD with Menu-Language in English / German / Finnish	-V09
LCD with Menu-Language in English / German / Chinese(b)	
LCD with Menu-Language in English / German / Russian	
LCD with Menu-Language in English / German / Hungarian	
LCD with Menu-Language in English / German / Serbian	
LCD with Menu-Language in English / German / Dutch	
LCD with Menu-Language in English / German / Romanian	
LCD with Menu-Language in English / German / Lithuanian	-V16
Tag No. Labeling	_
Stamped With Weather Resistant Color	
Stainless Steel Label Fixed With Wire	L

- (a) ONLY WITH (additional Inputs/Outputs E) AND (Optional Feature -B)
- (b) Not released
- (c) Only with Input/Communication D, H
- (d) Only with Input/Communication F, H, P and Q
- (e) NOT WITH (electrical certification ZZZ, EA4, EAA, GA4, GAA)
- (f) Available WITH (Version: C) AND (Built-in Limit Switch: S, D) AND (Electrical Classification: ZZZ, EA4, EAA, GA4, GAA, NFM, FAA) OR WITH (Version: B) AND (Built-in Limit Switch: S, D) AND (Electrical Classification: ZZZ, EA4, EAA, GA4, GAA, NFM, FAA)
- (g) Available ONLY WITH (Electrical Classification:FAA, NFM, CAA)
- (h) Available WITH (Version: B) OR WITH (Version: C) AND (Optional Features: S)
- (j) ONLY WITH (Built-in limit switch -S) AND (Electrical Classification EAx, NFM, FAA, GAx)
- (k) Only with ELECTRICAL CLASSIFICATION EA4, EAA or ZZZ
- (I) NOT WITH (optional feature -N OR Z OR Z1)
- (m) Available WITH (Version: C) AND (Built-in Limit Switch: S, D) AND (Electrical Classification: ZZZ, EA4, EAA, EDA, ED4, GA4, GAA, NFM, FAA) AND (Optional feature -S) NOT WITH (Optional feature -B)
- (n) Only with Version -C
- (s) Only available with Optional Feature LCD (-V01 to -Vxx) (u) Only with Electrical Classification: ZZZ
- (v) Only available for Input/Communication F, H, P and Q in connection with Electrical Classification ZZZ, FAA, NFM, EAA, CAA & GAA
- (w) Only available for Version single-acting -B in connection with Input/Communication -D and -H (x) Only in connection with Optional Features -B
- (y) Not with Optional Features -B
- (z) Not available with Electrical Classification FAA, NFM and CAA
- (1) On request



<sup>\*</sup> Unused threads for pressure are closed by means of lock screw Part No. 425 024 013

PSS EVE0105 E-(en) SRD991 23

# **MODEL CODES Accessories**

010414

	UT
Accessories for intelligent Positioners	
Filter Regulators	
Filter Regulator FRS923-2SK Filter Regulator for –40°C to 80°C	FRS01
Filter Regulator Filter Regulator for –20°C to 70°C	FRS02
Filter Regulator Stainless Steel (316) Filter Regulator	
Mounting Bracket for FRS02 or FRS03	
Orientable Mounting Bracket for FRS02 or FRS03	
Nipple for direct mounting Filter regulator 1/4 NPT both sides	
Communication / Modem / DTM	
HART USB Modem (made by Ifak) with ATEX IS Certification	MOD900
DTM for SRD Serie for HART / FF / Profibus / FoxCom	
ATEX IS Barrier Rail Mounted Module, 1 Channel, ATEX Ex ia IIC / FM Intrinsically Safe (TV228-SE	EGX) . TV228
Booster Relay	
Booster Cv 1 - Alu Housing - Remote mount(f)	VBS100
Booster Cv 1 - SST Housing - Remote mount(g)	
Booster Cv 7 - Alu Housing - Remote mount(b)	
Booster Cv 7 - SST Housing - Remote mount(b)	VBS310
Booster Relay with connection 1/4-18 NPT	I FXG-G
Booster Relay with connection G 1/4	
•	
Surge / Lightning Protection	DUCC L1
Surge/Lightning Protection for 4-20 mA with or without HART type TP48-N-NDI	BUSG-L1
	BUSG-L4
Lock-in Relays	
Lock-In Relay for lost of air supply for single acting / NAMUR Mounting	
Lock-In Relay (Fail Freeze) for lost of air supply and electric power for single and double actin	
SRI990 direct mounting	
Lock-In Relay for lost of air supply for single and double acting / direct mounting	LEXG-VR8
wirelessHART module	
WirelessHART Module Type Mactek BULLET for PST Monitoring (no Ex)	BUSG-WH1
WirelessHART Module Type Mactek BULLET for PST Monitoring (Intrinsically Safe ATEX+FN	
Cable Gland	,
Cable Gland, M20x1.5 Plug-Connector For Fieldbus (ss/Threaded Connection 7/8 - UN)	BUSG-F2
Cable Gland, M20x1.5 Plastics, Color Gray / Black	
Cable Gland, M20x1.5 Plastics, Color Blue	
Cable Gland, M20x1.5 Plastics, Color White	
Cable Gland, M20x1.5 Plug-Connector For Fieldbus (ss/Threaded Connection M12)	
Cable Gland, M20x1.5 HF For Fieldbus	
Cable Gland, M20x1.5 Stainless Steel	
Tube Fittings	VO 04
Tube Fittings, G 1/4 A, 6x1mm , 1 pc	
Tube Fittings, G 1/4 A, 6x1mm, 2 pcs	
Tube Fittings, G 1/4 A, 6x1mm, 3 pcs	
Tube Fittings, 1/4 NPT, 6x1mm, 2 pcs	
Tube Fittings, 1/4 NPT, 6x1mm, 3 pcs	VG-53
Adapter	
Adapter (Brass With Nickel Coating) M20 x 1.5 to 1/2 - 14 NPT (Internal Thread)	
Adapter (ss) M20x1.5 to 1/2-14 NPT (Internal Thread)	
Adapter (ss) M20x1.5 to G 1/2" (Internal Thread)	
Adapter (Plastic) M20x1.5 to PG13.5 (Internal Thread)	AD-A9
1	

# **MODEL CODES Attachment kits**

012007


ACCESSORIES FOR POSITIONER (SRD991, SRI990, SRD960)		0.2307
Attachment Kit		EBZG
For diaphragm actuators with casting yoke acc. NAMUR (incl. standard Couple lever)		
For diaphragm actuators with pillar yoke acc. NAMUR (incl. standard Couple lever)		
For directly mounting (incl. standard Couple lever)		D
For mounting to rotary actuators acc. VDI/VDE 3845 (without bracket)		
For FoxTop/FoxPak		
Brackets VDI/VDE 3845 (A = 130 mm / 5.12 in; B = 50 mm / 1.97 in)		C3
Brackets VDI/VDE 3845 (A = 80 mm / 3.15 in; B = 30 mm / 1.18 in)		C2
Brackets VDI/VDE 3845 (A = 80 mm / 3.15 in; B = 20 mm / 0.79 in)		C1
For Badger Meter - Research Control Series 754 and 755 Size 1/2 inch		
For Fisher 657, 667 (linear) size 30 and 40		
1051, 1052, 1061 size 40		
657, 667 size 30 and 60		
657, 667 size 70 and 100		
1051, 1052, 1061 size 33		
1051, 1052, 1061 size 60		
For Foxboro P-Series / such as -H with installed height 80 mm (3.15 in)		
NAMUR-Attachment kit for centered mounting position on the casting yoke		
For mounting on ADAR control valve		
Micro flow control valve		
Such as -K with installed height 80 mm (3.15 in)		
For Kinetrol (Actuator Size 05)		
(Actuator Size 07)		
(Actuator Size 09)		
For Metso / Neles Rotary actuators Type AB6 and Type BJ & BC size 8 and 10, B1C11  Type BJ and BC size12 and 16, B1C17		
For ARI-Armaturen - Direct Mounting to actuator type DR		
For ARCA - Direct Mounting to actuator type BR 812		
For Samson Type 3277 with 1/4 - 18 NPT		-91
Type 3277 with G 1/4		
Type 3277 with 1/4 - 18 NPT and gauges for supply and output pressure		
Type 3277 with G 1/4 and gauges for supply and output pressure		
Microflow Type 3277-5		
Tuflin/XOMOX Type MX60		
Type MX200		
Type MX450 / Type MX750 / Type MX1250		
Type MX3000		
For Hagan actuators (left of pneumatic cylinder)		X2
(right of pneumatic cylinder)		
For AMRI rotary actuator (requires minor modification of actuator. Please consult us before	ordering!) .	X3
For Siemens actuators V-Series		
For Sereg Maxflo, Revca, Reglob new type		
Maxflo "old type"		
CNX (Flowserve)		
For Masoneilan Type Camflex II		
47/48 (Sigma-F)		
Type 37/38 size 15 and 18 (complete kit)		
Type 87/88 all sizes		
Varipac		
37/38 size 9, 11, 13		
/Severn Glocon Type Domotor size small		
For Valtek Linear Actuator all Sizes - Stroke up to 4 inch / 102 mm		
For VETEC Type R150		VZ

<sup>\*)</sup> We recommend to contact our field service dept. before selection of these mounting kits. Further Attachment kits on request.

PSS EVE0105 E-(en) SRD991 25


# **MOUNTING TO LINEAR ACTUATORS**

Attachment to stroke actuators acc. to IEC 534-6 (NAMUR), left hand




### **MOUNTING TO LINEAR ACTUATORS**

Direct attachment to stroke actuators




# **MOUNTING TO LINEAR ACTUATORS**

Attachment to stroke actuators acc. to IEC 534-6 (NAMUR), right hand




### **MOUNTING TO ROTARY ACTUATORS**

Delivery of bracket by manufacturer of actuator




# DIMENSIONS - Attachment to rotary actuators acc. to VDI/VDE 3845




# MOUNTING acc. to VDI/VDE 3847

Mounting to Linear actuators



# Mounting to Rotary actuators



29

SRD991

### **DIMENSIONS**

Components of Attachment kits (samples)


# Feedback lever Code EBZG-A for 8 to 70 mm travel




Feedback lever Code EBZG-B for 60 to 120 mm travel



Feedback lever Code EBZG-E for FlowPak/FlowTop




Feedback lever Code EBZG-A1 for 100 to 260 mm travel





Carrier bolt for connection to valve stem



# Mounting bracket








mm in

### Weights of LEXG manifolds


LEXG -F =	0.90 kg
LEXG -F1 =	1.00 kg
LEXG -G =	1.25 kg
LEXG -G1 =	1.38 kg
LEXG -H =	1.40 kg
LEXG -H1 =	1.55 kg
LEXG -J/-J1 =	0.40 kg
LEXG -M/-M1 =	0.45 kg
LEXG - N - N1 =	0.28 kg
LEXG -K =	0.12 kg

### **DIMENSIONS**



SRD991 3

# **DIMENSIONS INOX** SRD991 in stainless steel housing



Invensys Systems, Inc. 38 Neponset Avenue Foxboro, MA 02035 United States of America

schneider-electric.com

Global Customer Support Toll free: 1-866-746-6477 Global: 1-508-549-2424

Website:

http://www.schneider-electric.com

Copyright 2010-2017 Invensys Systems, Inc. All rights reserved.

Invensys, Foxboro, and I/A Series are trademarks of Invensys Limited, its subsidiaries, and affiliates. All other trademarks are the property of their respective owners.

Life Is On Foxboro.

DOKT 534 022 074 FW18 i01 FD-PSS-PO-02-EN